

2 Channel Loop Amplifier



A compact mixer for driving a 75m² inductive loop, providing hearing aid users with high quality sound.

- 2 Microphone or line inputs
- Input and output connection via PCB mount screw terminals
- Built-in siren for evacuation alert
- Tamper proof channel volume
- Bass & treble and loop current level controls
- Peak current LED indication
- Vox priority
- Mounting brackets supplied
- Metal loss correction

Power Supply	230Vac, 50Hz	Input sensitivity: Line	-6dBu, 8kΩ
Frequency Response	50Hz - 5kHz	Input sensitivity: Mic	-56dBu, 2kΩ
Signal to noise ratio	75dB	Dimensions (HxWxD)	264x242x88mm
THD	≤1%	Weight	4.06kg

449917.439518

Order Code		Price Each
129-4332		