

		Device Programmers and Development Tools for Microcontrollers																																				
Home	Products	E-Shop	Support	Contact	News	Site Map																																
Quick Links Help Desk Downloads All Programmers Device Search Tools Catalogs  Shopping Cart Items: 0 Total: \$0.00 Your Account		AE-Q100-A3064 DIP40/QFP100 specialized adapter for Altera devices.  Description: DIP40/QFP100 specialized adapter for Altera devices. Device package dimensions: body - 14.0 x 14.0 x 1.0 mm, body with pins - 16.0 x 16.0 mm, 0.5 mm pitch. Supported Devices: Click the device programmer model below to get an appropriate list of the devices supported by this programmer with this adapter: ChipProg-48 ChipProg-G4 Adapter wiring diagram Adapter Connection Table: <table><thead><tr><th>DIP -40</th><th>TQFP-100</th><th>C1, 0.1uF</th><th>C2, 0.1uF</th></tr></thead><tbody><tr><td>11</td><td>4</td><td></td><td></td></tr><tr><td>12</td><td>15</td><td></td><td></td></tr><tr><td>20</td><td>38,86,11,26,33,43,53,59,65,74,78,95</td><td>1</td><td>1</td></tr><tr><td>27</td><td>62</td><td></td><td></td></tr><tr><td>32</td><td>39,91,3,18,34,51,66,82</td><td>2</td><td></td></tr><tr><td>34</td><td>73</td><td></td><td></td></tr><tr><td>39</td><td>88</td><td></td><td>2</td></tr></tbody></table>					DIP -40	TQFP-100	C1, 0.1uF	C2, 0.1uF	11	4			12	15			20	38,86,11,26,33,43,53,59,65,74,78,95	1	1	27	62			32	39,91,3,18,34,51,66,82	2		34	73			39	88		2
DIP -40	TQFP-100	C1, 0.1uF	C2, 0.1uF																																			
11	4																																					
12	15																																					
20	38,86,11,26,33,43,53,59,65,74,78,95	1	1																																			
27	62																																					
32	39,91,3,18,34,51,66,82	2																																				
34	73																																					
39	88		2																																			
Products Development Tools ARM 8051 Other Device programmers All Models Universal In-System Gang Adapters Custom made tools OEM tools																																						
Copyright © 2007-2010 Phytion, Inc. Phone: 718-259-3191 • E-mails: info@phyton.com , sales@phyton.com , support@phyton.com																																						