


Econoseal J Series [Mark II+] (Continued)

Wire Seals and Cavity Plugs

One wire seal is required for each contact.
Cavity plugs are used to seal unused connector cavities.



Description	Wire Range mm ² /AWG	Wire Ins. Dia. mm/Inches	Material & (Color)	Style	Wire Seal Part Number	Use With Contact Part Number	
Wire Seals	0.2-0.5 [24-20]	1.4-2.4 [.055-.094]	NBR (Black)	A	172746-1	171631-1 171631-2 173600-1	
		1.4-2.1 [.055-.083]		B	178210-1	171630-1 171630-5 171699-1	
	0.50-1.25 [20-16]	2.0-2.6 [.079-.102]	NBR (Gray)	C	172886-2	171661-1 171661-2 173706-1	
				D	176886-2	171662-1 171662-4 171662-5 173707-1	
		2.0-2.6 [.079-.102]		E	172748-1	—	
					172748-2	—	
Cavity Plug	—	—	NBR (Black) NBR (Gray)	E	172748-1 172748-2	—	

Wire Seals and Cavity Plugs . . . Dimensional Data

