Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234

www.tripplite.com

# SmartPro UPS System - Intelligent, line-interactive battery backup and network power management

### MODEL NUMBER: SMART1400RM

### **Description**

Tripp Lite's SMART1400RM UPS System provides intelligent, line-interactive battery backup for network devices and servers. 1,400 VA of battery backup allows you to work through short blackouts or safely shut down during longer ones. The unit has 8 outlets, diagnostic LEDs and 2 built-in serial ports that work with PowerAlert Software to provide simultaneous automatic unattended shutdown of multiple servers. Tripp Lite's PowerAlert Software is the only UPS software capable of managing every type and brand of UPS on your network, from every manufacturer. \$50,000 Ultimate Lifetime Insurance (USA & Canada Only). No warranty cards required for coverage!

#### **Features**

- 1,400 VA output power rating (940 watts)
- 8 protected outlets; 6 ft. cord
- Rackmount fits standard 19 in. rack (3 rack spaces)
- EXCLUSIVE from Tripp Lite: 2 DB9 serial ports to manage 2 network servers simultaneously;
   SNMP-compatible
- PowerAlert Unattended Shutdown Software and 2 (6 ft.) network cables included
- EXCLUSIVE from Tripp Lite: PowerAlert Software compatible with every brand of UPS, from every manufacturer
- Line-interactive with 4 levels of automatic voltage regulation (AVR)
- · Complete surge protection and EMI/RFI noise filtering
- \$50,000 Ultimate Lifetime Insurance (USA & Canada Only) -- No warranty cards required for coverage!
- Diagnostic LEDs (indicate 17 performance conditions)
- Hot-swap battery replacement

### **Specifications**

ОИТРИТ	
Frequency compatibility	60 Hz
Output VA	1400
Output watts	940
Output nominal voltage	120 V AC
Output voltage regulation	LINE MODE: Sine wave line voltage 120V (-12% / +5%) BATTERY MODE: PWM sine wave output 120V +/-5%
Output frequency regulation	LINE MODE: Passes line frequency of 60Hz +/-10% BATTERY MODE: Inverter output regulated to 60Hz +/-0.5Hz
Overload protection	Resettable circuit breaker
Outlet quantity / type	8 NEMA 5-15R

### **Highlights**

- 8 outlets provide battery backup and surge protection
- Automatic Voltage Regulation (AVR) corrects brownouts and overvoltages without draining battery power
- Two serial ports and free software facilitate unattended shutdown and network-wide power management
- \$50,000 Ultimate Lifetime Insurance (USA, Puerto Rico & Canada only)

### **Applications**

 Corporate and departmental servers, UNIX servers/workstations, hubs/routers/gateways/bridges, CAD/CAM/CAE workstations, network workstations, small-business servers, personal computers, and more.

### **Package Includes**

- SMART1400RM UPS System
- PowerAlert Software and 2 (6 ft;.)
   network cables
- Warranty information
- Instruction manual



Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

Customized load management receptacles	"1 individually controllable outlet supports automated load shedding and remote reboot on demand of locked network devices. Configurable via PowerAlert software to automatically switch off optional loads, like monitors, to increase available runtime for servers and other critical devices."	
INPUT		
UPS Input cord length (ft.)	6 ft.	
Recommended Electrical Service	15A 120V	
Input connection type	NEMA 5-15P	
Voltage compatibility (VAC)	120	
BATTERY		
Battery Access	Battery access door allows hot swap battery replacement without powering connected equipment off	
Full load runtime	10 minutes (1400VA)	
Half load runtime	26 (700VA)	
Typical battery lifespan	3-6 years, depending on usage	
Battery charge	2-4 hours to 90%	
VOLTAGE REGULATION		
Voltage regulation description	Line interactive UPS offers 2 boost levels of brownout correction and a single level of overvoltage adjustment to maintain usable, computer grade output without consuming battery power.	
Overvoltage correction	Input voltages between 127 and 140V AC are reduced by 10%	
Brownout correction	Input voltages between 95 and 105V AC are boosted by 12%	
Severe brownout correction	Input voltages between 87 and 94V AC are boosted by 22%	
Direct pass through	Input voltages between 110 and 127V AC are passed through unchanged	
LEDS ALARMS & SWITCHES		
Alarms	4 function audible alarm indicates power failure conditions (4 short beeps every 10 seconds), overload (continuous short beeps) and low battery (continuous tone)	
Switches	Yes, includes 2 front panel mounted push-button switches for system enable, self-test and alarm cancel	
Front panel LEDs	Yes, 5 front-panel indicator LEDs confirm line power, battery power, voltage regulation, load level and battery low / replace status	
SURGE / NOISE SUPPRESSION		
UPS AC suppression joule rating	Conforms to IEEE 587 / ANSI C62.41 specifications	





EMI / RFI AC noise suppression	Yes	
AC suppression response time	Instantaneous	
PHYSICAL		
Shipping weight (lbs)	43	
Shipping weight (kg)	19.5	
Unit Dimensions (HWD/in)	5.25 x 15.75 x 10.5	
Unit Dimensions (HWD/cm)	13.3 x 40 x 26.7	
Unit weight (lbs)	43	
Unit weight (kg)	19.5	
Cooling method	Convection	
Material of construction	PVC	
Form factors supported	3U rackmount	
ENVIRONMENTAL		
Relative Humidity	0 to 95%, non-condensing	
COMMUNICATIONS		
Network monitoring port	Two built-in DB9 communications ports (1 RS232, 1 contact closure) for use with PowerAlert software and cabling	
SNMP compatibility	Voc. with CANADIANED COLO external adenter accessory	
5	Yes, with SNMPWEBSOLO external adapter accessory	
Software and cabling included	Includes PowerAlert Plus software and 2 monitoring cables	
Software and cabling	Includes PowerAlert Plus software and 2 monitoring cables	
Software and cabling included	Includes PowerAlert Plus software and 2 monitoring cables	
Software and cabling included  LINE / BATTERY TRANS  Transfer time from line	Includes PowerAlert Plus software and 2 monitoring cables  FER	
Software and cabling included  LINE / BATTERY TRANS  Transfer time from line power to battery mode  Low voltage transfer to	Includes PowerAlert Plus software and 2 monitoring cables  FER  Battery Door / Hot Swappable	
Software and cabling included  LINE / BATTERY TRANS  Transfer time from line power to battery mode  Low voltage transfer to battery power  High voltage transfer to	Includes PowerAlert Plus software and 2 monitoring cables  FER  Battery Door / Hot Swappable  Maintains output from battery power as line voltage drops to 87V or less	
Software and cabling included  LINE / BATTERY TRANS  Transfer time from line power to battery mode  Low voltage transfer to battery power  High voltage transfer to battery power	Includes PowerAlert Plus software and 2 monitoring cables  FER  Battery Door / Hot Swappable  Maintains output from battery power as line voltage drops to 87V or less	
Software and cabling included  LINE / BATTERY TRANS  Transfer time from line power to battery mode  Low voltage transfer to battery power  High voltage transfer to battery power  SPECIAL FEATURES	FER  Battery Door / Hot Swappable  Maintains output from battery power as line voltage drops to 87V or less  Maintains output from battery power as line voltage increases to 140V or higher	



Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

WARRANTY		
Product Warranty Period (Worldwide)	2-year limited warranty	
Optional Coverage	3-5 year warranties, plus next day and on-site warranty coverage available for select opportunities. Contact Tripp Lite for additional information.	
Connected Equipment Insurance (U.S., Canada & Puerto Rico)	\$50,000 Ultimate Lifetime Insurance	

© 2014 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.

## **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Tripp Lite:

SMART-1400RM