



| JKL LAMP NUMBER | VOLTS RATED | AMPS ±10% | MSCP ±25% | LUMENS ±25% | AVERAGE LIFE HRS. | FILAMENT TYPE |
|--------------------|----------------|--------------|--------------|----------------|----------------------|------------------|
| 51 | 7.5 | .220 | 1.00 | 12.57 | 1,000 | C-2R |
| 53 | 14.4 | .120 | 1.00 | 12.57 | 1,000 | C-2V |
| 1445 | 14.4 | .135 | .70 | 8.80 | 2,000 | C-2V |
| | 18.0 | .150 | 1.50 | 18.86 | 250 | |
| 1450 | 24.0 | .035 | .23 | 2.89 | 3,000 | C-2F |
| 356 | 28.0 | .170 | 3.50 | 44.00 | 500 | C-2F |

| | | | | | | | | | | | |
|--------------------------|--|--|--|--|---|--|---|-----------------------------------|---|-------------|------------------------|
| | | | METRIC THIRD ANGLE PROJECTION | | DIMENSIONS ARE IN MILLIMETERS TOLERANCE UNLESS OTHERWISE SPECIFIED 1 PL +/- 0.2 2 PL +/- 0.20 ANGLE +/- 0 | | JKL COMPONENTS CORPORATION TITLE G-3 1/2 SINGLE CONTACT BAYONET BASE LAMP | | | | |
| DRAWN BY L. WENGSTROM | | | APPVD BY QC | | DATE 3/8/01 | | SIZE A | FSCM NO. 55335 | DRAWING NO. BAYONET SINGLE CONTACT G-3 1/2 | | |
| RELEASED AS CAD | | | 3/8/01 | | - CAD DRAWING - MANUAL REVISIONS NOT PERMITTED | | SCALE NONE | RELEASED DATE 3/8/01 | REVISION DATE | REV. NO. | SHEET 1 OF 1 |

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[JKL Components:](#)

[51](#)