



# Dialog 4220 Lite Dialog 4222 Office Dialog 4223 Professional

System Telephones for MX-ONE™  
Telephony System and MD110

Dialog 4223 Professional only for D3 mode

## Quick Reference Guide

This Quick Reference Guide includes short descriptions on how to use the basic features. To learn more about all available functions and features, please see the related User Guide.

### Free Seating<sup>1</sup>

Log on: \*11\* Authorization code \*  
Own ext. No. #

Log off: #11#

### Answer Calls

Answer:

Handsfree: Press flashing Line key  
(Dialog 4222 and 4223 only)

On another extension  
(Call pick-up): Call ringing ext. 8  
France: 4; Sweden: 6

End call: or

### Make Calls

Internal calls: Ext. No.

External calls: External line code and No.

Handsfree: Dial No.  
(Dialog 4222 and 4223 only)

Common Speed  
Dialing number: Dial Speed Dialing No.

Individual Speed  
Dialing number: \*\*(0-9)  
Finland: \*(1-9); Sweden: (0-9) #

Dial by a function  
key: Press the preprogrammed key, e.g.  
Head office

Last External  
Number Redial: \*\*  
Finland, Sweden: \*\*0

### Dial-by-name<sup>1</sup>

Example; "Eva": Dir 3 3 8 8 8 Find  
(Dialog 4223 only) UP or Down Call

**Aastra**

The complete User Guide is available in electronic format on the Enterprise Telephone Toolbox CD and on <http://www.aastra.com>

### Dialing during a connected call

Switch to DTMF: 9 Dial requested digits  
Finland: 1 Dial requested digits

### Inquiry

Ongoing  
conversation: Inquiry Call 3rd party

Refer back: Line 1 or Inquiry

Return to first  
party and finish  
Inquiry: Line 1

### Transfer

Ongoing  
conversation: Make Inquiry  
Transfer (Before or after answer)

### Conference

Ongoing  
conversation: Make Inquiry 3 (After answer)

### Callback

Activate: 6   
Finland, France, Sweden: 5

Cancel single  
Callback: #37\* Ext. No. #

Cancel all  
Callbacks: #37#

### Call Waiting

Activate: 5 (At busy tone) Wait on line  
Finland and France: 6; Sweden: 4

### Handsfree

(Dialog 4222 and 4223 only)

From handset:

Back to handset:

### Diversion

Order from your  
own extension

Diversion or \*21#   
(Diversion key is preprogrammed)  
U.K.: \*2#

Cancel: Diversion or #21#   
U.K.: #2#

### Internal Follow-me

Order from your  
own extension: \*21\* New ext. No. #   
U.K.: \*2\*

Cancel: #21#   
U.K.: #2#

Redirect from  
answering  
position:

\*21\* Own ext. No. \*  
New ext. No. #   
U.K.: \*2\*

Cancel from  
answering  
position: #21\* Own ext. No. #   
U.K.: #2\*

### External Follow-me

Order: \*22# External line code and No.  
#

Cancel: #22#

### Personal Number<sup>1</sup>

Activate or  
change profile from  
own extension: \*10\* (1-5) #

Cancel: #10#

### Voice Mail<sup>1</sup>

Enter your  
mailbox: Dial voice mail No. and follow recorded  
instructions

New message  
received: Press preprogrammed Message key  
and follow recorded instructions

### Programming of Function Keys

Program or change  
a function: Program Press selected function key  
No. or code Press function key again  
Program

Subject to alteration without prior notice. For more information, please  
contact your Aastra Certified Sales Partner.

### On Hold

Individual: Line

Resume call: Line

Common hold: 8   
France: 4; Sweden: 6

Resume call on  
own ext.: Line

Resume call on  
another ext.: Call the extension where the call was put  
on hold 8  
France: 4; Sweden: 6

### Account Code<sup>1</sup>

New external call: \*61\* Account code #  
External line code and No.  
Finland and Norway: \*71\*

Ongoing external  
call: Line \*61\* Account code  
# Line  
Finland and Norway: \*71\*

### Absence Information<sup>1</sup>

Order:

With return  
date/time: \*23\* Absence code \*  
Date/Time #   
(Date sequence is system dependent)

Without return  
date/time: \*23\* Absence code #

Cancel: #23#

### Choice of Language<sup>1</sup>

Change display  
language: \*08\* Language code (0-9)  
#

### Silent Ringing

Switch off ring  
signal:

### General Deactivation

Cancel all activated  
features: #001#

### Abbreviations and Explanations

ext. Extension

No. Number

1 Feature may be optional

© Aastra Telecom Sweden AB 2008. All rights reserved.  
EN Part of LZV 103 002 R5A