

◦ RJ-45/HDMI Receiver (non-powered)

Suitable as a short-range receiver (up to 10m) converting from RJ-45 to HDMI. This non-powered device plugs directly into a monitor's HDMI socket.

Note: some displays (particularly Samsung brand products) require a power source to function correctly; in this case please use the powered product below.

- **HDMI-HR** - receiver (non-powered)




◦ RJ-45/HDMI Receiver (powered)

A powered version of the above product. This is required on some brands of flat screen displays, particularly Samsung products.

- **ET-HC0101-Z** - receiver (powered)



Typical Configuration (at 1080p):



◦ HDMI 4 Way Selector Switch

This 4-into-1 HDMI switch selects between four HDMI sources, providing one output. Ideal for retail stores, conference rooms, home theatre, etc. The source material is easily switched via a slimline remote control.

Features:

- Three switch modes - automatic, manual or remote control
- HDMI 1.3a & HDCP compliant
- Supports full 1080p HD
- Built-in EQ for fine tuning
- **SW-H00401-H** - HDMI 4 way switch



Specifications:

Model:	SW-H00401-H:
Description	4-into-1 HDMI switch
AV Inputs	HDMI x 4
AV Outputs	HDMI x 1
Resolution	480i, 480p, 720p, 1080i, 1080p
Cable Extension	20m
Remote Control Distance	10m
Power	5v DC
Dimensions	23(H) x 198(W) x 80(D) mm

Typical Configuration:

