

SPECIFICATION SHEET**JFW MODEL 50PD-110****2 WAY RESISTIVE POWER SPLITTER**

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Frequency Range	DC-3000 MHz
Impedance	50 Ohms nominal
Return Loss	20 dB minimum
Equivalent Source Match	25 dB minimum DC-2000 MHz 20 dB minimum 2000-3000 MHz
Insertion Loss	6.02 dB nominal
Amplitude Tracking	± 0.25 dB
RF Input Power	1 Watt average @ 25°C
RF Connector	N male (input) N female (outputs)
Physical Size	See outline drawing 092-2169

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	01/26/1995						
9999	11/15/2002	A	SL 11/27/2002				