



■ Features :

- Protections: Short circuit / Overload / Over voltage
- Cooling by free air convection
- LED indicator for power on
- 100% full load burn-in test
- * All using 105°C long life electrolytic capacitors
- * Withstand 300VAC surge input for 5 second
- High operating temperature up to 70°C
- Withstand 5G vibration test
- High efficiency, long life and high reliability
- 3 years warranty

SPECIFICATION



MODEL		RT-125A			RT-125B			RT-125C			RT-125D		
	OUTPUT NUMBER	CH1	CH2	CH3	CH1	CH2	CH3	CH1	CH2	CH3	CH1	CH2	CH3
ОИТРИТ	DC VOLTAGE	5V	12V	-5V	5V	12V	-12V	5V	15V	-15V	5V	24V	12V
	RATED CURRENT	12A	5.5A	1A	12A	5A	1A	10A	4.5A	1A	8A	3A	2A
	CURRENT RANGE Note.	2 ~ 15A	0.5 ~ 6A	0.1 ~ 1A	2 ~ 15A	0.5 ~ 6A	0.1 ~ 1A	2 ~ 15A	0.5 ~ 6A	0.1 ~ 1A	2 ~ 15A	0.4 ~ 4A	0.1 ~ 2/
	RATED POWER Note.6	131W		132W		132.5W		136W					
	RIPPLE & NOISE (max.) Note.	80mVp-p	120mVp-p	80mVp-p	80mVp-p	120mVp-p	120mVp-p	80mVp-p	150mVp-p	150mVp-p	80mVp-p	150mVp-p	120mV
	VOLTAGE ADJ. RANGE	CH1: 4.75 ~ 5.5V			CH1: 4.75 ~ 5.5V			CH1: 4.75 ~ 5.5V			CH1: 4.75 ~ 5.5V		
	VOLTAGE TOLERANCE Note.	±2.0%	+8,-3%	+6,-10%	±2.0%	+8,-3%	±6.0%	±2.0%	+8,-3%	±6.0%	±2.0%	±5.0%	±6.0%
	LINE REGULATION Note.	4 ±0.5%	±1.0%	±1.0%	±0.5%	±1.0%	±1.0%	±0.5%	±1.0%	±1.0%	±0.5%	±1.0%	±1.0%
	LOAD REGULATION Note.	±1.0%	±3.0%	±6.0%	±1.0%	±3.0%	±6.0%	±1.0%	±3.0%	±6.0%	±1.0%	±3.0%	±6.0%
	SETUP, RISE TIME	500ms, 2	500ms, 20ms/230VAC 1200ms, 30ms/115VAC at full load										
	HOLD UP TIME (Typ.)	25ms/230VAC 30ms/115VAC at full load											
INPUT	VOLTAGE RANGE	88 ~ 132VAC / 176 ~ 264VAC selected by switch 248 ~ 373VDC(Withstand 300VAC surge for 5sec. Without damage)											je)
	FREQUENCY RANGE	47 ~ 63H:	<u>z</u>										
	EFFICIENCY (Typ.)	79%			80%		81% 82%						
	AC CURRENT (Typ.)	3A/115V/	AC 2A	/230VAC									
	INRUSH CURRENT (Typ.)	COLD ST	TART 40A/2	30VAC									
	LEAKAGE CURRENT	<2mA/2	<2mA / 240VAC										
PROTECTION		110 ~ 150% rated output power											
	OVERLOAD	Protection type : Hiccup mode, recovers automatically after fault condition is removed											
	OVERVOLTAGE	CH1: 5.75 ~ 6.75V											
	OVER VOLTAGE	Protection type: Hiccup mode, recovers automatically after fault condition is removed											
ENVIRONMENT	WORKING TEMP.	-25 ~ +70	5 ~ +70°C (Refer to "Derating Curve")										
	WORKING HUMIDITY	20 ~ 90%	20 ~ 90% RH non-condensing										
	STORAGE TEMP., HUMIDITY	-40 ~ +85	-40 ~ +85°C, 10 ~ 95% RH										
	TEMP. COEFFICIENT	±0.03%/°C (0 ~ 50°C)on +5V output											
	VIBRATION	10 ~ 5001	10 ~ 500Hz, 5G 10min./1cycle, period for 60min. each along X, Y, Z axes										
SAFETY &	SAFETY STANDARDS	UL60950-1, TUV EN60950-1 approved											
	WITHSTAND VOLTAGE	I/P-O/P:3KVAC I/P-FG:2KVAC O/P-FG:0.5KVAC											
	ISOLATION RESISTANCE	I/P-O/P, I/P-FG, O/P-FG:100M Ohms / 500VDC / 25°C/ 70% RH											
(Note 7)	EMC EMISSION	Compliance to EN55032 (CISPR32) Class B, EN61000-3-2,-3											
	EMC IMMUNITY	Compliar	Compliance to EN61000-4-2,3,4,5,6,8,11, EN61000-6-2 (EN50082-2), heavy industry level, criteria A										
OTHERS	MTBF	209.3Khr	s min. M	IL-HDBK-2	17F (25°C))							
	DIMENSION	199*98*3	8mm (L*W*	H)									
	PACKING	0.7Kg; 20	0.7Kg; 20pcs/14Kg/0.8CUFT										

- 3. Tolerance: includes set up tolerance, line regulation and load regulation.

 4. Line regulation is measured from low line to high line at rated load.

 5. Load regulation is measured from 20% to 100% rated load, and other output at 60% rated load.

 6. Each output can work within current range. But total output power can't exceed rated output power.
- 7. The power supply is considered a component which will be installed into a final equipment. All the EMC tests are been executed by mounting the unit on a 360mm*360mm metal plate with 1mm of thickness. The final equipment must be re-confirmed that it still meets EMC directives. For guidance on how to perform these EMC tests, please refer to "EMI testing of component power supplies." (as available on http://www.meanwell.com)

 8. Length of set up time is measured at cold first start. Turning ON/OFF the power supply very quickly may lead to increase of the set up time.



